



D1255RB Fire Keypad



The D1255RB Fire Keypad is a full-function system controller and annunciator. This SDI bus compatible device works with the Bosch GV2 Series control panels (firmware version 7.04 and higher). The illuminated keypad has a 16-character vacuum fluorescent display (VFD) with each character a 14-segment unit and a sounder that emits distinct condition tones.

Functions

Display

The display uses words, numbers, and symbols to show the status of the fire system. When several events occur, each event is shown in order of priority followed by the time of occurrence. In conjunction with the 16-character VFD, four LEDs provide the following system status indications:

- Fire
- Silenced
- Supervisory
- Trouble

Keys

The keypad has ten numeric keys and five function keys. Use the [COMMAND] key with the numeric keys to perform a function. Use the [ENT] key or [YES] key to enter your passcode. When pressed, each key emits light and a muted beep.

- ▶ **Compatible with Bosch GV2 Series control panels (firmware version 7.04 and higher)**
- ▶ **Built-in multi-tone sounder**
- ▶ **Easy to read vacuum fluorescent display (VFD) shows complete system status in English**
- ▶ **Easy system control with menu keys**
- ▶ **User controlled brightness and volume**
- ▶ **Installer configured menus, text, and custom functions**
- ▶ **Multiple or single area configurations**

Audible Tones

The sounder emits distinct warning tones. You can adjust the volume or use a passcode to silence the tone. The tones include:

- Fire signal: pulsed high-pitched bell tone during fire alarm
- Invalid key buzz: buzz tone when invalid key is pressed
- Keypad encoding tone: muted beep tone as each key is pressed
- Trouble buzz: two-tone warble during a trouble event

Certifications and Approvals

Region	Certification	
USA	UL	UOXX: Control Unit Accessories, System (ANSI/UL 864)
	FM	
	CSFM	7165-1615: 119 Control Unit (Non High-Rise) and 7170-1615: 145 Control Unit (High-Rise)

Installation/Configuration Notes

Compatible Control Panels

The D1255RB Fire Keypad is compatible with the D9124GV2, D7412GV2, and D7212GV2¹ control panels with firmware version 7.04 or higher. The keypad will work with G Series Control Panels prior to GV2 v7.04; however the LEDs will not operate.

¹ The D7212GV2 is not listed for commercial fire applications.

Mounting Considerations

The keypad is a low profile, surface-mounted unit molded in durable red plastic with three mounting holes in the base that allow secure, correct positioning during installation. Protect the surface-mounted keypad by mounting it to a D56 or D56R Conduit Back Box. For desktop applications, the keypad can be mounted to a D55 Desk Stand.

Note Do not install the keypad in direct sunlight. This damages the module components and makes the display less visible. Do not mount in wet or moist locations.

Wiring Considerations

The keypad connects to the control panel for data and power through a standard four-wire flying lead cable. For field wiring use 0.8 mm (22 AWG) or 1.2 mm (18 AWG) wires. Resistance cannot exceed 25 Ω. The field wiring connects to a four-wire harness supplied with the unit.

Note Use shielded cable where excessive electromagnetic interference is a problem.

Parts Included

Quantity	Component
1	Keypad
1	Hardware pack
1	Literature pack

Technical Specifications

Environmental Considerations

Relative Humidity:	5% to 85% non-condensing at +30°C (+86°F)
Temperature (operating):	0°C to +50°C (+32°F to +122°F)

Mechanical Properties

Color:	Red and gray
Dimensions:	11.7 cm x 21 cm x 2 cm (4.6 in. x 8.2 in. x 0.8 in.)
Material:	CHI MEI POLYLAC PA757 ABS with UV Stabilizer. UL94-HB Fire Rated

Power Requirements

Current:	104 mA minimum, 225 mA maximum
Voltage:	12 VDC nominal supplied by the control panel

Trademarks

Due to the nature of this material, this document refers to hardware and software products by their trade names. In most, if not all cases, these designations are claimed as trademarks or registered trademarks by their respective companies in one or more countries. It is not Bosch's intent to use any of these names generically. The reader is therefore cautioned to investigate all claimed trademark rights before using any of these names other than to refer to the product described.

POLYLAC is a registered trademark of CHI MEI Industrial Corporation, LTD. Plexiglas is a registered trademark of Arkema.

Ordering Information

D1255RB Fire Keypad Red and gray case.	D1255RB
Accessories	
D55 Keypad Desk Stand Portable desk stand in smoke colored Plexiglas.	D55
D56 Surface Mount Conduit Box White surface mount box.	D56
D56R Red Surface Mount Conduit Box Red surface mount box.	D56R

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: +31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6258 5511
Fax: +65 6319 3499
apr.securitysystems@bosch.com
www.boschsecurity.com

Represented by